

Radio  
Receivers

Remotes

Gate  
Controllers

Gate  
Automation  
Accessories

Gate  
Motors

Access  
Control



**WIRELESS**

**AUTOMATICALLY  
BACKLIT  
KEYBOARD**

## KEYPOINT

- simple operation
- durable housing for outdoor installation
- 259 control channels in two radio systems  
DTM868MHz and DTM433MHz
- sound signaling

KEYPOINT allows wireless control of many automation devices by selecting one of the many codes available on the numeric keypad. Battery power supply allows installation in any place. Durable and thoughtful housing design allows installation in places exposed to vandalism inside and outside buildings.

## Parameters

frequency: 433MHz i 868MHz  
number of control channels: 4 channels 433MHz and 255 channels 868MHz  
maximum radio range: 150 m  
power supply: 2x battery 3,6VAA  
battery performance: 3 years with 10 cycles per day  
keyboard: made of PC, 12 backlit keys  
housing: plastic, ASA  
IP: IP54  
installation: surface-mounted  
working temperature: -10°C / +55°C  
dimensions: 110x75x40 mm  
weight: 140 g

## Functionality

control: each of the 259 channels is activated after entering the individual code. The code is made from 1 to 4 digits long.  
special code: one code, thanks to which it is possible to control channels by entering their number, without having to enter an individual code  
sound signaling: audio messages indicating that the button has been pressed, the operation is successful or failed, and the device has been blocked  
protection against entering incorrect code: function blocking access to the device for a minute after entering the wrong code three times  
keyboard backlight: built-in lighting and proximity sensor. The keyboard lights up when your hand is close to the keyboard. If the sensor function is turned off, the backlight is activated by pressing the button.  
battery status: low battery status signaled by an audible signal

Radio  
Receivers

Remotes

Gate  
Controllers

Gate  
Automation  
Accessories

Gate  
Motors

Access  
Control

