



NEW!

## IRS variable rolling code

- frequency **868MHz**
- modulation **FSK**
- customized security solutions  
**against radio intrusion**
- **intelligent adaptation**  
to radio conditions  
of transmitter  
and receiver

available versions:




FOR  
EASY GATE  
CONTROLLER

PART OF  
DTM868MHz  
SYSTEM

- easy installation
- simple programming
- power supply via gate controller
- compatible with DTM868MHz remotes

## EasyRX 868

It is a three-channel radio card in the new DTM868MHz system, which sets a new dimension of security. The use of modern technologies has made it possible to obtain a more reliable radio range, and the IRS 104-bit coding system protects the radio system against radio intrusion and unauthorized interference. It is designed for the implementation of radio control to DTM System EASY gate controllers.



# EasyRX 868

3-channel radio card for gate controllers

## ➤ Basic parameters

power supply: via gate controller  
memory capacity: 200 DTM868MHz series remote controls with an individual number in memory  
operating temperature (min./max.): -20°C/+55°C  
external dimensions (W x H x H): 55x40x13mm  
assembly method: through mainboard connector  
weight: 10g

## ➤ Outputs

output type / quantity: digital output / 1

## ➤ Radio parameters

radio module: modern, digital, superheterodyne with intelligent adaptation to external radio conditions, ensuring high reliability, repeatability and optimal sensitivity  
transmission security: 104-bit IRS  
type of modulation / frequency: FSK / 868MHz  
antenna input impedance: 50 Ω  
antenna: wire antenna, terminals for connecting an external antenna

## ➤ Functionality

user interface: interface on three LEDs and three buttons  
configuration of the remote: the ability to assign any of the two receiver channels to any button  
the ability to delete all memory: yes  
the ability to delete a single remote control: yes, deleted remote control presence necessary  
possibility to add the remote control without access to the receiver buttons: yes, the function of easy remote adding  
blocking the easy remote control adding function: yes

Radio  
Receivers

Remotes

Gate  
Controllers

Gate  
Automation  
Accessories

Gate  
Motors

Access  
Control



automation systems

DTM System, ul. Brzeska 7, 87-145 Bydgoszcz, POLAND, tel./fax +48 52 340 15 83, e-mail: dtm@dtm.pl  
[www.dtm.pl](http://www.dtm.pl)

